

IN THE CLAIMS

Please amend the claims as follows:

1. (Original) A current source adapted to produce an output current comprising:
first and second circuit branches connected between first and second reference voltages,
the first branch including a branch resistor connected at a junction node to a compensation
resistor which is connected to the second reference voltage; and
a start-up circuit connected to generate a start-up current at the junction node whereby the
voltage across the compensation resistor increases with the first reference voltage and acts to
reduce changes in the output current with the first reference voltage.
2. (Original) A current source according to claim 1, wherein the first circuit branch
comprises first and second series-connected bipolar transistors, the base of the first transistor
being connected to its collector.
3. (Original) A current source according to claim 2, wherein the second circuit
branch comprises third and fourth series-connected bipolar transistors, the third bipolar transistor
being connected as a current mirror with the first bipolar transistor and the fourth bipolar
transistor being connected as a current mirror with the second bipolar transistor.
4. (Presently Amended) A current source according to claim 2, ~~or 3~~, which
comprises an output transistor having its base connected to the base of the first transistor, the
collector current of the output transistor constituting the output current.
5. (Presently Amended) A current source according to claim 2, ~~3 or 4~~, wherein the
branch resistor is connected between the junction node and the emitter of the second transistor.
6. (Presently Amended) A current source according to ~~any preceding claim~~, 1,

Attorney's
Docket No.: S01022.80999

Express Mail Label No.: EV 292 548 241 US

- 6 -

wherein the start-up circuit comprises a pair of start-up transistors connected in a current mirror configuration and a start-up resistor connected between the collector of one of said start-up transistors and said junction node.

7. (Original) A current source according to claim 3, wherein the area of the second transistor is larger than the area of the fourth transistor.